

Opening and changing instructions for the  
F50 La Gard LG Master Digital Lock

CHANGING YOUR CODE MUST ALWAYS BE DONE  
WITH THE DOOR OPEN

Codes consist of an I.D. and a 6 digit number  
i.e 01 – I.D. plus code 111111

Default Manager code from factory is 01- 111111

There are 49 User I.D.'s available  
The Manager is always 01

To Open Lock

Press any button to power up lock.

Enter your 2 Digit I.D. and 6 Digit code, the lock will now open.

To Change Manager or User codes.

Press any button to power up lock.

Enter your 2 Digit I.D and six (6) zeros e.g. 01 000000

The screen will display an I.D. and request the old code for this I.D.

Enter the old code

The screen will display an I.D. and request a new code for this I.D.

Enter the new code once and a second time to confirm.

Test code. An I.D. must always be entered with the code.

TEST YOUR CODE AT LEAST 3 TIMES BEFORE  
CLOSING THE DOOR

SUPPORT

Contact Smartlock Digital 02 8338 4774 (Lock distributors)

Or

CMI Safe Co 02 9547 1488 (Safe Manufacturers)

**Manager Menu Instructions**  
**For the**  
**F50 La Gard LG Master Digital Lock**

Accessing Manager Menu:

Press any button to power up lock.  
Press and HOLD down OK button until screen displays “MANAGER”  
Enter the Manager 6 digit code to access the menu.  
( I.D. not required as you are in Manager mode)  
Use the P button to scroll options  
Use the OK button to access the options  
To exit, scroll through to “Do you want to quit” and press OK.

Users On /Off

After accessing the manager menu Users On/Off will display  
Press OK  
Select a User I.D. (e.g.) 02  
If this User does not exist. The screen will display 02 DELETED ! INSTALL  
To install press OK, then enter the code for this User twice.  
If this User already exists. The screen will display. 02 ENABLED ! DISABLE  
To disable this User press OK.  
To completely DELETE this user  
Press P to scroll past and screen will display 02 ENABLED ! DELETE  
To delete this User press OK.

SUPPORT  
Contact Smartlock Digital 02 8338 4774 (Lock distributors)  
Or  
CMI Safe Co 02 9547 1488 ( Safe Manufacturers)

**Master Menu**  
**8 Digit code required**  
Lock leaves factory set on master of 12345678

Press any button to power up lock.

Hold down zero (0) until MASTER displays, enter master code.

Use 'P' button to scroll options.

Use 'OK' to access or confirm the options

Allows access to menu

Time / Date setup

Time Lock standard week program. 7 day open & close programming

Time lock special events. One off modify 7 day program

Manager: Delete or Install

Loss of Master code denies access to the above and  
can only be corrected by the complete lock returning to the factory for resetting.

PC Link & System setup menus: Service technicians only.